

Components for Control Stations or Distribution Boxes

◆ Ammeter/Voltmeter unit (B for short)



Catalogue number logic

B - A □(□/□)

Ammeter range
Type
Ammeter
Ammeters/Voltmeters

B - V □(□)

Voltmeter range
Type
Voltmeter
Ammeters/Voltmeters



Main technical data

	Ammeter (A for short)		Voltmeter (V for short)	
	Type 48	Type 72	Type 48	Type 72
Accuracy	Level 1.5			
Specification	0.1A, 0.5A, 1A, 1.5A, 3A, 5A, 7.5A, 10A 15A, 20A, 25A, 30A, 40A, 50A, 60A, 75A, 100A		30V, 50V, 75V, 100V, 120V, 150V 200V, 250V, 300V, 400V, 450V	
Note: connect to the attached current transformer of secondary current of 5A or 1A, the ammeter is overload meter, overload current is 5 times, 3 or 2 times can be supplied upon request, if there're any special requirements, please specify.			Note: connect to the attached current transformer of secondary voltage of 100V.	

Note: please specify the type, measuring range, current ratio and voltage ratio when ordering.